## CAUTION

Before starting to use your Move sensor, please read the complete instructions manual carefully, especially the safety instructions on our website: www.alogo.io/docs.

Before using for the first time, please charge your Move sensor for 3.5 hours with the supplied USB cable.

#### Included in the Box

Sensor: Alogo Move Pro.

**USB cable:** To charge your sensor.

**Hook:** To attach your martingale or your training aids to your girth.

**Measuring tape:** To measure the distance between the sensor and the

ground the first time the sensor is used on a new horse.

(More info in the complete manual).

#### Quick Start guide.

Sensor holder supplied separately.

## **INSTALLATION**

#### 1. Fasten to the girth

### Positioning of the sensor

(make sure that the sensor is facing in the right direction)

### **Ground:**

Face toward the ground


### Horse:


Face against the horse



ALOGO MOVE PRO The sensor must be placed underneath the horse at the center, and facing in the correct direction.

**Attention:** Any adjustments to the girth should be done equally on both sides so that the sensor remains in a central position.





## USE

To start recording a session.

#### Without smartphone

- Turning ON: Press the power button for 1.5 seconds until the red LED lights up. You can start recording when you see the pink LED.
- Recording: Press the power button once. The LED turns green and blinking, indicates the start of the recording.
- Stop: You can stop the recording by pressing once the power button of your Move sensor.
- 4. Turning OFF: The sensor automatically turns off after 2 minutes if no movement is detected. You can switch it off by pressing the power button for 1.5 seconds until the red LED lights up.



When the sensor is connected to a power source, the LED displays the charging status in green. If the battery level is low, the blinking will become slower. The LED will turn OFF when the battery of your sensor is fully charged.

To start recording a session.

#### With smartphone

Please note: Bluetooth must be active on your smartphone.

#### 1. Turning ON:

Press the power button for 1.5 seconds until the red LED lights up.

#### 2. Launch the "Alogo" app:

Or download it from the AppStore or Google Play.

- Create an account if you haven't already done so or log in with your credentials.
- Settings tab

Press "Sensor management" and select your Move sensor.
The LED will blink blue once the connection is established.
The next time the phone is used, it will automatically connect to the sensor that was last selected.

#### 3. Recording:

Press the "Recording" button in the interface.

#### 4. Stop:

Press the "Stop" button in the interface. You can also stop the session by directly pressing the power button on your Move sensor.

### 5. Turning OFF:

The sensor automatically turns off after 2 minutes if no movement is detected. You can switch it off by pressing the button for 1.5 seconds until a red LED lights up.

To turn it off from the app, go to Settings > Sensor management > Select your sensor > Turn off.

#### **Disconnection during recording**

Your Move sensor works independently from the mobile app. In case you lose your Bluetooth connection, your session continues to be recorded on the internal memory of your sensor.

# ADDITIONAL **INFORMATION**

Your Alogo Move Pro sensor has a built-in GPS chip. The accuracy of the GPS depends on several environmental factors such as weather, location and whether you are indoors or outdoors. If GPS reception is poor, for example in an indoor arena, some data will not be displayed. For more information, please refer to the instruction manual.

### Safety instructions:

Do not expose your Alogo Move sensor to any violent impacts, such as dropping or throwing the device. Do not place magnetized objects near the Alogo Move sensor for long periods of time, as this may cause irreversible damage to the sensor.

After use, store the product in a dry place. Never attempt to disassemble or reassemble your product yourself. All repairs must be carried out by a representative certified by Alogo Analysis SA.

We recommend that you use your Alogo Move sensor in a temperature range between -20°C and +50°C (-4°F and 122°F). Prolonged use outside of this temperature range may cause irreversible damage to components, especially the battery, and provide inaccurate data.

The sensor is equipped with an internal lithium polymer battery (3V, 3000mAh). If used improperly, the internal battery may explode or release dangerous chemicals. Never disassemble, crush or puncture the battery. Do not dispose of it in fire or water.

Communication is wireless via Bluetooth Low Energy 4.2+, 2.4Ghz Protocol. The transmission speed and range of the sensor with your smartphone depends on the distance between them and any other obstacles in between, such as the horse, a person or a wall,

Alogo Analysis SA Switzerland


www.alogo.io







## **SYNCHRONISATION**




## 1. Training

Once your session(s) are over, the recordings are stored in the memory of your Move sensor.



5. Display on a Smartphone / PC / Tablette





2. Sensor



In order to view them, please open the "Alogo" application so that your sessions are synchronized with your smartphone and sent to our Cloud. Your phone needs to have an active internet connection.



## RECOMMENDATIONS

- We recommend to switch on your sensor before the riding session and to begin recording it when you start to work the horse.
- The recording length of a session will have an impact on the Bluetooth transfer time.
- In order to obtain the most accurate data, don't place any metallic or magnetic accessories around the sensor when in use.
- Do not immerse the sensor in water or any other liquid.

